

PDU & Maintenance Bypass Switch

Features

- 16A for 208/220/230/240 VAC
- Provides continuous power to connected equipment during UPS maintenance
- Easy operation with simple rotary switch and indicators
- Master-slave function for energy saving
- Provides a large number of sockets for multiple connections
- Provides rack and tower designs to fit into a diverse working environment
- Simple installation with plug-and-play socket type
- Suitable for all UPS Units up to 3KVA



PDU & Maintenance Bypass Switch Selection Guide

MODEL		MBS RACK	MBS TOWER
Current Rating		16 A max. for 208/220/230/240 VAC	
Voltage Rating		208/220/230/240 VAC	
Master/Slave Function		Yes. When power consumption in Master outlet is lower than 20W ($\pm 5W$), it will shut off the power for slave outlets.	NA
CONNECTION			
Input	AC Power	1 x IEC (16 A) connector and 1 x customized plug cable	
	UPS Input	1 x IEC (16 A) connector and 1 x cable (16A - 10A IEC cable for 1K/2K, 16A - 16A IEC cable for 3K)	
	UPS Output	1 x IEC (16 A) connector and 1 x cable (16A - 10A IEC cable for 1K/2K, 16A - 16A IEC cable for 3K)	
Output	IEC	5 x IEC 10A sockets + 1 x IEC 16A socket (with 2 circuit breakers)	8 x IEC 10A sockets + 1 x IEC 16A socket (with 2 circuit breakers)
PHYSICAL			
Dimension	DxWxH(mm)	80 x 438 x 50	180 x 160 x 50
Net Weight (kgs)		1.5	1.3
ENVIRONMENT			
Operating Temperature		20-95 % RH @ -5-45°C (non-condensing)	

* Product specifications are subject to change without further notice

